

# Scimagic Auto Scan RF Multi Frequency Universal Remote Control Duplicator

Best position for duplication



## Feature

### Auto scan type

Multi frequency 280-868mhz  
Duplicate rolling code and fixed code  
Up to 4 different remotes in 1

## Programming

### A) Standard

1. Press and hold button 1 and press button 2 four times at same time
2. Release 2 buttons till LED flashed once every three seconds
3. Put original remote in the front of new remote (about 2-3cm), press the original remote button which need to be copied until the LED of new remote flash quickly (LED have regular flashes)
4. Press the button of New remote that you want to use to save the code
5. If you do not copy successfully, please repeat above steps
6. To duplicate a second button, repeat the above steps

### B) Automatic matching code

After copy successfully, don't use any remote first, then put the new remote close to the receiver to active it, press and hold the button until the Led of it flash quickly, then you can try it

### Emitting seed code

Pressing the button 1 and button 2 at the same time until LED flashes quickly. Release 2 buttons, press the button that you want to emit seed code, it has emitted seed code successfully

## AMC: Automatic Matching Code

### BFT

- 1) Press and hold button 1 and press button 2 four times at same time, Release 2 buttons till LED flashed once every three seconds
- 2) Put original remote in the front of new remote (about 2-3cm), press and hold the original remote button which need to be copied until the LED will turn on with a fixed light and then emits a double flash very 2 seconds
- 3) Pressing the hidden button or the button 1 and 2 simultaneously in the new models (transmit the seed code of original BFT remote)
- 4) Now the led will flash quickly, press the new remote button that you want to save the code, the LED will off
- 5) Now active the remote with AMC procedure

### FAAC and GENIUS

Note: your original remote control must be in a master version

How to recognise a master/slave transmitter:

master: if you press any key of a master transmitter, the LED flashes before becoming steady.

slave: if you press any key of a slave transmitter, the LED goes on immediately with steady light

- 1) Press and hold button 1 and press button 2 four times at same time, Release 2 buttons till LED flashed once every three seconds
- 2) Put original remote in the front of new remote (about 2-3cm), press and hold the original remote button which need to be copied until the LED will turn on with a fixed light and then emits a double flash very 2 seconds
- 3) Pressing and hold the button 2 and 3 simultaneously of original FAAC/GENIUS to transmit the seed code
- 4) While the led of FAAC and GENIUS is flashing, put it close to new remote about 2-3cm, and press the button that you want to copy until the LED will change the frequency of flash (faster than before to confirm the correct copy the code)

### V2

- 1) Press and hold button 1 and press button 2 four times at same time, Release 2 buttons till LED flashed once every three seconds
- 2) Put original remote in the front of new remote (about 2-3cm), press and hold the original remote button which need to be copied until the LED will turn on with a fixed light and then emits a double flash very 2 seconds
- 3) Press and hold once again the same button of original remote, the LED of new remote will flash quickly, press the button that you want to save the code, until the LED off
- 4) Now active the remote with AMC procedure

## Compatible List

Brand	Model	Brand	Model
ACM (AMC)	TX2, TX2 COLOR, TX4	KEY	900TXB-42R, SUB44, TXB-44R, TXG-44R
ADYX	TE4433H BLUE, 433-HG BRAVO	KINGGATES	STYLO, CLIPPER
AERF	COMPACT, HY-DOM, MERCURI B, MERCURI C, SABUTON, MARS, SATURN, ST3/N, TERRA, TMP-1, TMP-2, UNITECH	KLING	KUA, KUA E, KUA S
		LABEL	SPYCO, RW4E
ALLMATIC (AMC)	BROWN, BROWN RED, BRO.OVER, PASS, MINIFASS	LEB	TMW
APERIO	GO, GO PRO, GO MINI	LINCE	LR2035
APERTO (SOMMER)	TX02-434-2, TX02-868-2 BLUE, 4025 TX02-868-2, 4022 TX02-434-2, 4020 TX03-434, TX-03-868-4, 4013, TX03-434-4	LIFE	LIFE FIDO2 / FIDO4 / VIP2 / VIP4 / VIP2R / VIP4R / STAR2 / STAR4 / BRAVO2 / BRAVO4
APRIMATIC (AMC)	TR2/TR4, TM4, TXM	LINEAR	MCT-11, ACT-22, ACT-21, STING RAY ACT-31, STING RAY ACT-34B
ATA	PTX4 BLUE, PTX4 PINK	MHOUSE (AMC)	GTX4, GTX4C, TX4
AVIDSEN	104251, 104250, 104250 OLD, 104250 RED, 104257, 104350, 654250	MA	TX1, TX2, TX3
		MOOVO (AMC)	MT4G

<b>BALLAN</b>	FM400, FM400E, FM404B, 4013	<b>MARANTEC</b>	D101,D12,DIGITAL302,DIGITAL304		
<b>BENINCA (AMC)</b>	TO.GO.WV, TWV, ROLLKEY, APPLE, LOT WCV, CUPIDO,TO.GO.QV, IO, LOT2WCV,LOT1W, LOT2W, LOT4W, LOT1WM, LOT2WM,T2W, T4W	<b>MERLIN/PROLIFT</b>	M230T(PROLIFT),M430R(PROLIFT)		
		<b>MERLIN 2.0</b>	E945M,E943M,E940M		
<b>BESIDE</b>	BEZAP, HIT	<b>MONSEIGNEUR</b>	ARC		
<b>BFT (AMC)</b>	MITTO, MITTO M(MITTO 2M/MITTO4M), MITTO RCB(MITTO RCB02/MITTO RCB04), MITTOA(MITTO 2A/MITTO 4A), MITTO B,TRC(TRC2/TRC4), GHIBLI, MURALE, KLEIO, TEO1, TEO2,TEO4, RB4 MURALE	<b>NORTON</b>	NEO, TXCD,GO NORTON,GO MINI NORTON		
		<b>NOVOTECNICA (AMC)</b>	BLXL2		
<b>CAME</b>	T431, T434, TOP432A, TOP434a, TOP432, TAM432SA, TOP432NA	<b>NOVOFERM</b>	NOVOTRON 502-504-512MIX43-2,MTX40-2,MCHS43-2,MHS43(2-4),MNHS433(2-4),MCHS, MINI-NOVOTRON504,MICRO-NOVOTRON		
<b>CARDIN (AMC)</b>	TRQ S449 (TRQ449100/TRQ449200/TRQ449300/TRQ449400), TRQ S449 GREEN(PRECODE), TXQ S449(TXQ449200/TXQ449300/TXQ449400), TXQ S449 GREEN, TRQ S486(TRQ486200/TRQ486400), TXQ S486(TXQ486200/TXQ 486200/TXQ486400), S437 TX, XRADO, S449, S476TX2, S476TX, S486	<b>NOLOGO</b>	ECO DIP		
		<b>O&amp;O (AMC)</b>	T.BOM,TWIN,TX,TWIN,TX2/TX4		
		<b>O&amp;G</b>	OG62,OG64		
<b>CASALI</b>	JA33 AMIGO, GENIUS/CASALI A252RC	<b>OPENOUT</b>	TMQ		
<b>CASIT</b>	ERTS92B, ERTS92T, ERTS476D, ERTS20DQ, ERTS476D, ERTS476Q	<b>PECCININ</b>	TX MENBRANA		
<b>CELISA</b>	S10 1, S10 2	<b>PORTAMATIC</b>	MPH01,MPH02		
<b>CENTURION</b>	CLASSIC, SMART	<b>PRATEL</b>	TC2E(4E),SLIM,BFOT,MPSTP2E,MPSTF2,MPSTF4,MPSTF2RE,MPSTF4RE,MPSTP2E,MPSTP2EBL UE		
<b>CHAMBERLIN/ LIFTMASTER/ MOTORLIFT</b>	953ESTD, 371LM(315MHZ), 81LM,971LM(390MHZ),84330E,94334CE, 94333E/94334E/94335E, 9747E, 1A5477, 1A6487, 132B2372, 94330EML/94333EML/94335EML, 84330EML/84333EML/84335EML, 8747EML			<b>PROEM</b>	ER4C4ACS
				<b>PROGET</b>	ETY_433N2,ETY_433N4
<b>CLEMSA</b>	MUTANCODE, T, T-8, E-CODE N, MASTERCODE MV	<b>PROTECO</b>	TX433,EUROMATIC		
<b>CPS</b>	TCP3, CPS1, CPS2, CPS4	<b>PUJOL</b>	MARTE,P215,TWIN,VARIO,VARIO MARS, VARIOOCEAN,NEO		
<b>DASPI (AMC)</b>	HAPPY2, POPS 2, ZERO RC(ZERO 2RC, 4RC)	<b>QUASAR</b>	433		
<b>DEA</b>	TR MIO, 133 1, 433 2, GENIE, PUNTO S2, PUNTO 278, GOLDR, GENIE R 273, GENIE R-GT2N	<b>RIB</b>	LITHILO		
<b>DELMA</b>	MIXARD 433 1, MIXARD 433 2, KING 433 2	<b>ROPER</b>	NEO,GO ROPER,GO MINI ROPER		
<b>DICKERT</b>	MAHS433 01, MAHS433 04	<b>SABUTOM</b>	BROOVER,BROSTAR		
<b>DITEC (AMC)</b>	GOL, GOL4C, BIXLS2, BIXLP2, BIXAG4, BIXLG	<b>SEA</b>	SMART DIP		
<b>DOORMATIC</b>	SAW	<b>SECULUX</b>	NEO		
<b>DOITRAND</b>	MPSTF2E, JAUNE	<b>SEAV</b>	BE HAPPY RS(BE-HAPPY-RS1,BE-HAPPY-RS2,BE-HAPPY-RS3),BE-SMART RSX,BE-HAPPY RH1,BE-HAPPY RH2,BE-HAPPY RH3		
<b>DOORHAN</b>	TRANSMITTER 4				
<b>DUCATI</b>	TSAW1, TSAW2, TSAW3, 124, TE2	<b>SILVELOX</b>	MHZ 2007, QUARZ SAW		
<b>ECOSTAR</b>	RSE,RSC,RSZ	<b>SICE</b>	4790207		
<b>ELBE</b>	501, 502, 504, 502A, 504A	<b>SIMINOR</b>	CVXNL,MITTO,SIM433		
<b>ERREKA</b>	IRIS, ROLLER 2, ROLLER 433, ROLLER 868, SOL433, SOL868, VEGA 433, VEGA 868	<b>SEUCURVERA</b>	SV R2C,SV R4C,SV R6C		
<b>ELCA</b>	IRIS, ASTER,ASTER 1000,ASTER 1001	<b>SERAI</b>	OG/52,OG54,OG82,OG84,OG/28,OG48,OG62,OG64		
<b>FAAC (AMC)</b>	XT 433 RC, TM1 433 DS, TM2 433 DS, TM3 433 DS, 433L2, 433L4, TM2 433 SLP, TM4 433 SLP, TLM 433SLH, TLM 868SLH, DL 868SLH, XT 868SHL, XT 433SHL, T 868SHL, T 433SHL, XT433RC, TE433HG	<b>SOMFY</b>	LEIS,K-EASY,K-EASY NEW,K-EASY OLD,MITTO,KEY GO RTS,TELIS,KEYTIS RTS		
<b>FADINI (AMC)</b>	FADINI JUBI, JUBI SMALL, ASTRO 43 SMALL, 433 M2 ASTRO 433-2, ASTRO 433-4, JUBI2/JUBI4	<b>SOMMER</b>	SOMMER 4026 TX03-868-2,SOMMER 4020 TX03-868-4,SOMMER 4031,SOMMER 4025,SOMMER 4011,SOMMER 4035,APERTO 4025		
<b>FERPORT</b>	TAC1,TAC2, TAC4, TAC 1K, TAC 2K, TAC 4K, TAC2KR	<b>STAGNOLI</b>	KALLISTO,VENUS AV223		
<b>GIBIDI</b>	GIBIDI OPEN TMB, OPEN OUT, AUO1590, AU1600, DOMI- NO AU1680 WOOD, GIBIDI AU1610,GIBIDI AU1680, AU1810, AUO3000,AUO3000 DOMINO,DTC 4334,DTS4334-AUO400	<b>TAU (AMC)</b>	250K-SLIMRP,250K-SLIMR,250T-4RP		
		<b>TELCOMA</b>	FM402,FM402E,FM400E,FM400		
<b>GULLIVER</b>	MDW	<b>TORLIFT</b>	TORMIT4		
<b>GENIUS (AMC)</b>	AMIGO,AMIGOLD,KILO,BRAVO,ECHO	<b>VDS (AMC)</b>	TRQ P,ECO-R		
<b>GENIE (AMC)</b>	GITR-3, GIT, GICT390, GIFT390-1, G3T-BX, G1T-BX, GM3T, GICTD, GIFTD	<b>VARWFORD</b>	EA433 4K,SMART2,SMART3		
<b>HORMANN</b>	HSM2,HSM4	<b>V2 (AMC)</b>	V2 PHOX 2, V2 PHOX 4,V2 PHOENIX 2,V2 PHOENIX 4,V2 TXC,V2 TRC,V2 TSC4,V2 HAND		
<b>JAY</b>	UBEI X 1SL1,UBET 21,UBET 41,UBET 61				
<b>KBLUE</b>	ETH-TEL01				