

Mhouse Manual

The programming manual is the same as original remote control. If our manual is not clear, you can search manual in google, youtube.also can contact us via Email. Anyway, we will try our best to make best service for you.

Below is the programming manual:

Memorization of the Transmitter in "Mode 1"

- On control units and receivers for gates

1. Press Button **P1 [H]** in Fig.3 for at least 3s; when the **P1 LED [I]** shown in Fig.3 goes off, release the button.
2. Within 10s, press any button on the radio transmitter to be memorized for at least 2s. If the memorization procedure is successful, the **P1 LED** will flash 3 times.
3. If there are other remote controls to be memorized, repeat step 2 within the next 10s, otherwise the memorization stage will terminate automatically.

Memorization of the Transmitter in "Mode 2"

- On control units and receivers for gates

1. Press button **P1** as many times as the number corresponding to the desired command, according to the table 2 (e.g. 3 times for the "Open only" command).
2. Make sure that the **P1 LED** flashes as many times as the number corresponding to the desired command.
3. Within 10s, press any button on the radio transmitter to be memorized for at least 2s. If the memorization procedure is successful, the **P1 LED** will flash 3 times.
4. If there are other remote controls to be memorized for the same type of command, repeat step 3 within the next 10, otherwise the memorization stage will terminate automatically.